

# MIX-6LIVE

STUDIO MIXER.



## DESCRIPTION

6-channel stereo mixer with live streaming function, PC audio card and Bluetooth®/USB recorder/player.

Live streaming function, you can connect your smartphone or tablet and broadcast your performance live on your favourite platform, no need for anything else.

Connect the mixer to your PC as an audio card. You can play audio content from your PC and record audio on your PC simultaneously.

Bluetooth®/USB recorder and player, play music or record your performance without a PC.

Includes 24-bit digital effects processor (16 effects) with effect selection and level control, which will give an extra touch to your performances.

It also features 48 V phantom power on channels 1 and 2 for use with condenser microphones.

It has a small and portable size, perfect for street performers, home music studios, small events or parties, etc. In addition, it only requires a 5V DC, 2.1A power supply, which can be provided by the adapter, by the USB port of a PC or laptop or through a power bank, which greatly increases the versatility and possibilities of use of this



Expand product information on:  
<https://fonestar.com/es/MIX-6LIVE>

complete mixer.

**TECHNICAL CHARACTERISTICS**

<p>FEATURES</p>	<p>Stereo mixer with 4 mono channels and 1 stereo channel.                  Live streaming function, connect your smartphone to broadcast live.                  USB audio input/output for PC connection as audio card, allows you to play audio from PC and record it simultaneously.                  Bluetooth receiver.                  USB recorder/player.                  16 digital effects processor.</p>
<p>USB PLAYER</p>	<p>Plays or records MP3 files                  USB-C port for connection to PC as an audio card                  Stereo line-level auxiliary input</p>
<p>INPUTS</p>	<p>4 balanced microphones/lines, combo (XLR, 600 Ohm 15 mV RMS and 6.3 mm jack, 47.000 Ohm 200 mV RMS)                  1 balanced stereo line channel, 2 x 6.3 mm jack, 47,000 Ohm 250 mV RMS                  1 stereo auxiliary, 3.5 mm jack, 47,000 Ohm 1 V RMS                  1 stereo auxiliary (live streaming), 3.5 mm TRRS jack, 47.000 Ohm 250 mV RMS                  1 microphone, 3.5 mm jack TS, 600 Ohm 15 mV RMS                  1 USB/PC, stereo</p>
<p>CONTROLS</p>	<p>6 controls per channel: gain, 3-band equalizer, pan, volume and clip indicator light                  Effects and level selection                  Headphone volume                  Independent volume control for main and aux/monitor output</p>
<p>FUNCTIONS</p>	<p>3-band equaliser per channel                  Overload indicator and master output level indicator light                  Live streaming                  USB/PC</p>
<p>OUTPUTS</p>	<p>1 balanced/unbalanced stereo main, 2 x 6.3 mm/2 jack x RCA, 2.5 V RMS                  1 balanced aux/monitor, 6.3 mm jack, 2 V RMS                  1 stereo aux (live streaming), 3.5 mm TRRS jack, 0.5 V RMS                  1 stereo headphones, 6.3 mm jack                  1 USB/PC, stereo</p>
<p>PHANTOM</p>	<p>48 V on channels 1 and 2, selectable</p>
<p>RESPONSE</p>	<p>20-20,000 Hz</p>



Expand product information on:  
<https://fonestar.com/es/MIX-6LIVE>

DISTORTION	Harmonic: 0.04 %
S/N RATIO	> 65 dB
POWER SUPPLY	5 V DC, 2.1 A with included adapter
DIMENSIONS	210 x 70 x 237mm depth
WEIGHT	1.1 kg
ACCESSORIES	3.5 mm TRRS male-to-male audio jack cable USB-A to USB-C power cable USB power adapter



Expand product information on:  
<https://fonestar.com/es/MIX-6LIVE>